

3000 MAH

2-CELL LIPO

TRAXXAS POWER CELL

TRAXXAS 2-CELL LIPO

3000 MAH

20C

7.4v

If you have any questions, call TRAXXAS Customer Support at 1-888-TRAXXAS (1-888-872-9927). Outside the US +1-972-549-3000

- NEVER leave batteries unattended during charging.
- Do NOT disassemble, crush, short circuit or expose to flame.
- Do NOT exceed the maximum recommended charge rate.
- ALWAYS confirm charger settings match this battery prior to charging, or use the battery.
- If any battery or cell is damaged in any way, do NOT charge, discharge, or use the battery.

- While charging, always place the battery in a fire retardant/fire proof container and on a non-flammable surface such as concrete.
- ALWAYS charge batteries in a well-ventilated area.
- REMOVE flammable items and combustible materials from the charging area.
- Use ONLY a Traxxas iD equipped Lipo charger with this battery. DO NOT charge with a NiMH only charger.

FIRE HAZARD!

Read and follow all manufacturer's charging and handling instructions, warnings and precautions before use! LiPo Batteries pose a severe risk of fire if not properly handled and charged per the instructions. Never allow children under 14 years old to charge batteries without the supervision of a responsible, knowledgeable adult.



WARNING! CAUTION! DANGER!



Part #2827X
Made in China
G002054-R00

Copyright © Traxxas 2023. All rights reserved.
Traxxas McKinney, TX
LITHIUM
RECYCLING
Patent Pending
Traxxas.com/pat



LiPo

2S 3000 20C 7.4V

Specifications:
 Configuration: 2s1p
 Continuous Discharge: 20C (60A)
 Max Burst Rate: 40C (120A)
 Watt Hours: 22.2
 Charge Rate: 1C (3.0A)
 Max Charge Rate: 2C (6.0A)
 Dimensions (mm): 135Lx25Hx44W
 Weight: 5.5oz (156g)



Traxxas Exclusive!
 The balance wires are integrated into the main connector for fast, easy, and rugged connection to Traxxas LiPo chargers. Fragile balance wires, balance boards, and tiny connectors are eliminated. A Traxxas LiPo charger is required for charging this battery.

TRAXXAS

LIPO

LITHIUM POLYMER BATTERY

3000 MAH

2-CELL

2S - 7.4 Volts 20C Sustained 40C Burst 2C Charge

Traxxas Certified to meet the power and top speed requirements of Traxxas models

iD

iD Auto Battery
 Identification
 PATENTED TECHNOLOGY

Use with Traxxas iD Chargers for the easiest and safest charging solution
Traxxas® iD™ chargers auto-detect iD equipped Traxxas batteries and automatically optimize charge settings for worry-free charging*

High-Current Connector with Gold-Plated Copper Terminals

Integrated LiPo Balance Charging Wires

MAXX® Cable High-Efficiency 12-Gauge Silicone Jacketed Wire

*Following manufacturer's instructions and warnings. Chargers sold separately.